



Connection Functions

At Terminal	Function
D/U D	Speech from door
D/U E	Speech to door
PSU 12	12v AC for ringing & lock
PSU 0	12v AC for ringing & lock
PSU +	12v DC for speech & lamps
PSU -	12v DC for speech & lamps
TEL A2	Ringer Warble
TEL A1	Ringer buzzer (if fitted)
TEL L	Speech from door
TEL P	Speech to door
TEL 4	Lock button
TEL B	Common for ringers
TEL F	Common for speech
TEL G	Common for buttons
TEL SW COM	Switch common
TEL SW OUT	Switch in OUT position
TEL SW IN	Switch in IN position
TEL LED-	RED LED negative
TEL DOI	GREEN LED Door Open negative

Plan 1	Provides Ringing, Communication and Door Release functions.
201S Phones	These have additional features, an ON/OFF (CHOS) button with Red LED, and DOI Door Open Indicator Green LED where a normally open door sensor is fitted. Set jumper for DOI mode, 1-2 Always active, 2-3 Active only when handset is off-hook.
Notes	Insert LINKS everywhere shown ●●. Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.
Entryphone Co. Ltd. 23 Granville Road, London, SW18 5SD U.K. T:020 8870 8635 www.entryphone.co.uk	

Title :	WDA_1_3_201S	
Date :	August 2017	Drawn by : TH
Application :	Plan 1 – Multi Button D/U – 201S	