



**Connection Functions**

At	Terminal	Function
D/U	D	Speech from door
D/U	E	Speech to door
PSU	12	12v AC for ringing & lock
PSU	0	12v AC for ringing & lock
PSU	+	12v DC for speech & lamps
PSU	-	12v DC for speech & lamps
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (if fitted)
TEL	L	Speech from door
TEL	P	Speech to door
TEL	1-4	Buttons
TEL	B	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons
IC7RU	CBP	Common button feed
IC7RU	N/O	Lock relay 'open' contact
IC7RU	N/C	Lock relay 'closed' contact
IC7RU	Com	Lock relay common contact

Plan 2 Intercom Phones Provides Ringing, Communication and Door Release with Internal Intercom to Porter. have twin ringers, so that they Warble when called from a door, and Buzz when called on internal intercom. Notes Insert LINKS everywhere shown ●●●. Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

WDA_2_3_204P	
Date : August 2017	Drawn by : TH
Application :	Plan 2 Porter Intercom