



Connection Functions

At	Terminal	Function
D/U	D	Speech from door
D/U	E	Speech to door
PSU	12	12v AC for ringing & lock
PSU	0	12v AC for ringing & lock
PSU	+	12v DC for speech & lamps
PSU	-	12v DC for speech & lamps
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (if fitted)
TEL	L	Speech from door
TEL	P	Speech to door
TEL	1-4	Buttons
TEL	B	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons
IC7RU	CBP	Common button feed
IC7RU	N/O	Lock relay 'open' contact
IC7RU	N/C	Lock relay 'closed' contact
IC7RU	Com	Lock relay common contact

Plan 3 Intercom Phones have twin ringers, so that they Warble when called from a door, and Buzz when called on internal intercom.
 Notes: Insert LINKS everywhere shown ●●●. Ringer Warble volume, all phones have a spindle at the top left corner.
 Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

Entryphone Co. Ltd. 23 Granville Road, London, SW18 5SD U.K. T:020 8870 8635 www.entryphone.co.uk

Title : WDA_3S_4_204	
Date : August 2017	Drawn by : TH
Application : Plan 3/4 Intercom – Single Button	